

SMC1SMC1050/N

TECHNICAL SPECIFICATIONS

Throat diameter Rated impedance Minimum impedance D.C. Resistance Power capacity * Program power Sensitivity **

Frequency range Recommended crossover Voice coil diameter Magnetic assembly weight Flux density BL factor 25 mm. 1 in. 8 ohms. 5.3 ohms @ 4.3 kHz 5.6 ohms. 60 w AES above 1 kHz 120 w above 1 kHz 108 dB 1 w @ 1m coupled to TD-250 horn 0.8 - 18 kHz 1 kHz or higher (12 dB/oct. min.) 44.4 mm. 1.75 in. 2.1 kg. 4.63 lb. 1.8 T 9.3 N/A

MOUNTING INFORMATION

Overall diameter	120 mm.	4.72 in.	
Depth	61 mm.	2.40 in.	
Mounting	Three M5 threaded holes, 12	M5 threaded holes, 120° apart	
	on 57 mm. (2.24 in.) diameter circle.		
	Two M5 threaded holes, 18	80º apart	
	on 76.2 mm. (3 in.) diameter circle.		
	Mounting hardware is supplied.		
Net weight	2.2 kg.	4.84 lb.	
Shipping weight	2.35 kg.	5.17 lb.	


MATERIALS

- Diaphragm: mylar.
- Voice coil: edgewound aluminium ribbon.
- Voice coil former: polyimide.
- Magnet: ferrite.

GENERAL DESCRIPTION




DIMENSION DRAWINGS



Notes:


*The power capacity is determined according to AES2-1984 (r2003) standard. Program power is defined as the transducer's ability to handle normal music program material. **Sensitivity was measured at 1 m distance, on axis, with 1 w input, averaged in the range 1-7 kHz.

This 1" compression driver features a lightweight mylar diaphragm that provides an excellent high frequency response with low harmonic distortion. Other key features of this model are its excellent sensitivity (108 dB) and its high power handling (60 w AES above 1 kHz). By the other hand, the coil-diaphragm assembly is easily field replaceable without soldering.



horn in anechoic chamber, 1w @ 1m.

FREQUENCY RESPONSE AND DISTORTION CURVES



Note: on axis frequency response measured coupled to TD-245 horn in anechoic chamber, 1w @ 1m.

Polígono Industrial Moncada II · C/. Pont Sec, 1c · 46113 MONCADA - Valencia (Spain) · Tel. (34) 96 130 13 75 · Fax (34) 96 130 15 07 · http://www.beyma.com · E-mail: beyma@beyma.com ·